

QAC1100



Atlas Copco QAC1100 Silenced Generator: Twinpower



General Information	50Hz	60Hz
Dimensions LxWxH (mm)	6060 x 2500 x 2600	6060 x 2500 x 2600
Mass (Wet - Ready to operate) (kg)	11 964	11 964
Fuel Tank Capacity (l)	1640	1640
Fuel Consumption at 75% Load (l/hr) to 100% Load (l/hr)	146 to 203	148 to 208
Frequency (Hz)	50	60
Prime Rated Power (Kva/KW)	1000 / 800	1000 / 800
Voltage (V)	400	440
Nominal Current (A)	1444	1374
Sound Power Level LWA dB (A)	72	73
Min/Max Ambient (°C)	-18/50	-18/50

Additional Accessories

Cables (Recommended 4 sets of 185mm 4 core + 1 x 95mm Earth Cable)	Distribution Boards	Transformers	External Fuel Tanks
--	---------------------	--------------	---------------------

Other features

9 Kg Fire Extinguisher	4-Pole Battery Isolator Switch	Emergency Stop Switch
Buzz Bar	Automatic Mains Failure (AMF) (Certain Fleet Models only)	Remote and Auto Start (Certain Fleet Models only)
External Fuel Tank Connection (Certain Fleet Models only)	Strobe Light (Indicating units is operational)	Spillage Free Frame
Paralleling with Compatible Generators	Specialized Eye Lifting Hooks	

Rand Air South Africa (Pty) Ltd

Part of the Atlas Copco Group	P.O. Box 13921	Atlas Copco House,	Tel: +27 (0) 345 0700
Company Reg. No. 2017/250308/07	Witfield 1467	Innes Road, Jet Park	Info@randair.com

For Information Only. Subject to change without notice. Information is for guidance only contact your nearest rental office for application advice .

2021-11-18